



## **Intrinsically safe LEDs indicator BA 386**

Red, yellow, green, blue and white alone installation or together with horn. Adjustable horn acknowledgment, after new alarm. IP56 housing.

## **Technical specifications BA 386**

### **Explosion protection**

Ex [ia] IIC T4

### **Electrical data**

Min. 10 V DC via safety barrier  
28V 93mA

Attention without safety barrier the  
Indicator can be damaged.

### **Rated current**

25mA or 40mA in combination with  
BA 385

### **Flash energy**

0,5 Joule

### **Frequency**

2 Hz

### **Safety specifications**

$U_0 = 28 \text{ V DC}$ ,  $I_0 = 110\text{mA}$ ,  
 $P_0 = 0,8\text{W}$

