



## **Intrinsically safe sounders BR 385**

49 different tones three-stage alarms up to 103dB (A). Sound pressure satisfies PFEER regulations. IP66 enclosure can be operated individually or with BR386 strobe light.

## **Technical specifications BR 385**

### **Explosion protection**

Ex [ia] IIC T4 Ga

### **Electrical data**

Min. 16 V DC via safety barrier

28V 93mA

Attention without safety barrier the sounder can be damaged.

### **Rated current**

25mA by 24V DC via safety barrier

### **Safety Specifications**

$U_o = 28V$  DC,  $I_o = 93mA$ ,

$P_o = 0,66W$

